CYGNETT

ROAM
200W/102.4Wh Portable Power Station



SKU: CY5867CYPPS

KEY FEATURES
Beyond everyday power: Ideal for weekends, festivals, and remote working. Perfect for charging laptops, tablets, phones, and other small devices.
Various charging options: 2x USB-A, 2x USB-C, 1x DC port, and 1x AC port for versatile device compatibility.
Fast charging: Each USB-C port delivers 65W, while the AC port delivers 200W for high-speed charging.
Long lifespan: Powered by LiFePO4 batteries with 3000+ charge cycles.
Lightweight and portable: Weighs just 2kg, easy to take anywhere.
Solar compatibility: Pair with any compatible solar panel for true off-grid independence.
Built-in LED light: Four light modes for camping, low light, or emergencies.
2 year warranty: Enjoy peace of mind with coverage for two years.

SPECIFICATIONS
1x AC Output: AC 220-240V, 50Hz, 200.0W (250.0W Surge Peak)
1x Car Charger Output: 12.6V 8A, 100.0W (max)
2x USB-A Outputs: 12.0W (max)
2x USB-C outputs: USB-C1: 30.0W (max), USB-C2: 65.0W (max)
Total Output: 200.0W (max)
AC Charging Power: 120.0W (max)
Solar Input: 12-24V 4A, 50.0W (max)
Car Input: 12V= 4A
AC + PV Charging Power: 120.0W

Product Size:
200mm H x 134mm W x 130mm D
Product Weight:
2000g

Packaging Dimensions:
225mm H x 170m W x 211mm D
Packaging Weight: 100g
Product Barcode: 848116053042

What's in the box:
1x 200W / 102.4Wh Power Station; 1x AC Power Cord Cable, 1x Car Charge Cable, Warranty Card, User Manual

PRODUCT HIGHLIGHTS:
Power made portable
Weighing just 2kg with a 102Wh capacity, this compact Power Station is built for convenience. With 65W USB-C and 200W

Backup power, built in
With Uninterruptible Power Supply (UPS), when the Power

AC output, it easily handles everyday essentials, from phones and laptops to fans, camping lights, and air pumps.	Station is plugged into the wall and the power goes out, it automatically switches to battery power, helping prevent interruptions or sudden shutdowns.
3,000 charge cycles Powered by LiFePO4 battery technology, delivering up to 3,000 full charge cycles for long-lasting reliability.	**Clear, real-time display** The front LCD screen shows state of charge (SOC) power and charge/discharge time, so you're always in control.
Clean power Pure sinewave inverters provide stable, consistent energy, so sensitive devices run safely and smoothly. No glitches, noise, or risk of damage.	**Built for off-grid use** Pair with Cygnett's 1000W Foldable Solar Panel to harness solar energy when you're away from a power outlet.